Forcorp Pty Ltd

PHASE ROTATION INDICATOR WITH FUSED HEADS



T855



Feature	Range
Input Voltage	200 to 600V AC
Frequency Range	50 to 60Hz
Operating Temp.	-10 to 40°C @ 80% RH
Fuses	0, 5A x 3 HRC
Compliance & Safety	EN61010 CAT IV 600V, CE
Contents	T855, Vinyl Case, crocodile clips on built in colour coded leads & instruction manual.

FEATURES AND BENEFITS

The T855 is suitable for line workers to check phase sequence on aerial electrical conductors. The log leads can easy reach across the phases and are fused for increased protection. The probes have pluggable crocodile clips for easy attachment to bare conductor.

- Live line indication
- Push button for motor rotation testing
- Heavy duty crocodile clips
- Test probes fused for extra protection, shrouded tips
- CAT IV 600V
- Phase sequence—clockwise rotation correct
- Long leads for overhead lines

CONTACT US FOR MORE INFORMATION

WEB: www.austutilities.com.au PHONE: 08 9406 3200

EMAIL: sales@forcorp.com.au

